

# **LSZDC**



- D150 / D500 SURVEILLANCE MODULE
- LOOP, IMPEDANCE AND DC MONITORING
- LOW STANDBY CURRENT

## **OVERVIEW**

The LSZDC is an amplifier interface card for use with the D500 and D150 Transformerless Class-D Amplifiers in a V2000 Amplifier Mainframe for Voice Alarm and Public Address applications. It enables two circuits (A&B) to be fed from a single amplifier while still maintaining BS5839 Pt 8 compliance.

This interface card provides

- · amplifier health monitoring via subsonic surveillance tone
- · standby switchover
- · loudspeaker line earth leakage monitoring
- · loudspeaker line 'End Of Line' (EOL) monitoring

Relays in series with each output facilitate isolation of faulty speaker circuits.

Loudspeaker circuits can be monitored using DC, Impedance or Loop Return methods.

Each LSZDC includes powerful on-board DSP (digital signal processing) capability, enabling parametric equalisation, gate and gain settings to be applied separately to each amplifier.





#### **SPECIFICATION**

#### Power

## **Audio Processing**

Gain .....-60 to +10 dB
Gate .....Configurable Threshold / Attack / Hold Release
EQ......10 Band Parametric

#### Interfaces

# **Environmental**

# Mechanical

 Dimensions
 64 mm x 30 mm x 121 mm

 Weight
 0.15 kg

 IP Rating
 IP20 as part of V2000 frame

CE

This equipment is designed and manufactured to conform to the following EU Directives:

Electromagnetic Compatibility (EMC)): 2014/30/EU
Low Voltage: 2014/35/EU
Restriction of Hazardous Substances (RoHS): 2011/65/EU

Manufacturer Application Solutions (Safety and Security) Limited Unit 17 Cliffe Industrial Estate Lewes - East Sussex BN8 6JL - UK

Tel: +44(0)1273 405411 www.asl-control.co.uk Fax: +44(0)1273 405415





Assessed to ISO 9001 LPCB Cert No: C1043