zenitel

DATASHEET

1200300000

INTEGRA-00

Système PAVA mural (sans canal d'amplification préinstallé)

- Certifié EN 54-16
- Système PAVA mural autonome
- Installation simple pour le montage des batteries
- Sans canal d'amplification pré-installé
- Jusqu'a 2000W @ 100V au total par INTEGRA
- Traitement audio professionnel de haute qualité
- Traitement audio 24 BIT 48 kHz
- 12 Entrées et sorties audio analogiques / 6 Entrées audio IP

Public Address Voice Alarm Commercial Audio Civil Defence Approval EN54 Certification EN54-16

Description

La solution d'alarme Audio Tout-en-Un INTEGRA-00 est disponible sans canal d'amplification préinstallé, mais qui peut être étendu ultérieurement.

Le système dispose de 12 entrées audio et d'une mémoire interne pouvant contenir jusqu'à 64 messages enregistrés. Avec une puissance maximale de 2000W, l'audio transite en IP et bénéficie d'un traitement audio puissant, un chargeur de batterie intégré et une étagère pour faciliter le montage de la batterie, le tout dans un coffret mural compact, INTEGRA fournit une solution d'alarme audio complète pour les systèmes PAVA centralisés et décentralisés de moyenne et grande taille.

Jusqu'à 32 INTEGRA peuvent être connéctés par IP pour permettre des diffusions à partir de n'importe quel endroit, vers n'importe quelle combinaison de zones, dans les systèmes décentralisés. Le switch réseau (NETWORK-SWITCH-LP01) forme une topologie de réseau en anneau conforme à l'alarme vocale et peut être facilement monté à l'intérieur du coffret

Toutes les variantes d'INTEGRA et la gamme VIPEDIA équivalente montées en rack interagissent de manière transparente

www.zenitel.com info@zenitel.com

Last revision date: 2026-01-20 09:54

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.

Spécifications

For full details see Documents

PUISSANCE

Tension d'alimentation AC	230V (+25% / -16%)
Fréquence d'alimentation en courant alternatif	50 / 60 Hz
Courant de repos (sans amplificateur)	525mA
Courant de repos (par amplificateur)	23mA
Puissance de sortie audio maximale	2000W

Accessoires

BMB01 from datasheet

BMB01

Extension GPIO RS485 sur rail DIN

Référence Produit: 1200550030

from site

D150

PAVA Module amplificateur de puissance 150W pour le V2000 / INTEGRA

Référence Produit: 1200202150

from site

D500

PAVA Module amplificateur de puissance 500W pour le V2000 / INTEGRA

Référence Produit: 1200202500

NETWORK-SWITCH-LP01

PAVA Network Switch - Layer 2

Référence Produit: 1200571000

LSZDC

PAVA Amplifier Interface Module for the V2000 / INTEGRA

Référence Produit: 1200540000

Zenitel and its subsidiaries assume no responsibility for any errors that may appear in this publication, or for damages arising from the information therein. Zenitel products are developed and marketed by Zenitel. The company's Quality Assurance System is certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.

ZENITEL PROPRIETARY. This document and its supplementing elements, contain Zenitel or third party information which is proprietary and confidential. Any disclosure, copying, distribution or use is prohibited, if not otherwise explicitly agreed in writing with Zenitel. Any authorized reproduction, in part or in whole, must include this legend; Zenitel – All rights reserved.