



### 3006220002

## 26103

U914T, Pocket Receiver with Display and Vibrator, 457.575MHz

- ✓ IP64: Durable design, Robust and shock resistant
- Message Alarm priority identified by the signal
- Group paging available
- Seven individually programmable beep signals and silent mode for meetings
- Reminder function that indicates at regularintervals that there are unread messages
- Easy to reprogram via storage/charging rack or radio
- Automatic out-of-range warning and battery test
- ✓ HF Frequency Band: H914T and UHF Frequency Band: U914T models

## Description

A robust pager designed for heavy usage in demanding environments. It is splash resistant and dust proof, in accordance with IP64 classification, plus impact resistant. Message priority indication, with distinct beep codes, helps to ensure that critical alerts are not missed.

Also available in an "intrinsically safe" model, designed for use in potentially explosive environments.

# Specifications

### **GENERAL**

Dimensions (LxWxD)	86x51x19 mm
Weight	84g including battery
Operating temperature	-10°C to +50°C
Message length	120 characters
Storage capacity	10 messages
Sound pressure level	> 93 dBA at 10 cm
Frequency range	425-470 MHz

### **PRODUCT VARIANTS**

U914T, Pocket Receiver with Display and Vibrator. 457.575 Mhz  U914T Pocket Receiver with Display and Vibrator 457.525 Mhz  EX U914T Pocket Receiver with Vibrator, without Display. 469.250Mhz  EX U914T Pocket Receiver with Vibrator, without Display. 469.250Mhz  EX U914T Pocket Receiver with Vibrator, without Display 412- 427 MHz  EX U914T, Pocket Receiver with Display and Vibrator. 457.575MHz  H914T Pocket Receiver with Vibrator, 27.3 Mhz			
Display and Vibrator 457.525 Mhz  EX U914T Pocket Receiver with Vibrator, without Display. 469.250Mhz  EX U914T Pocket Receiver with Vibrator, without Display 412- 427 MHz  EX U914T, Pocket Receiver with Display 412- 427 MHz  EX U914T, Pocket Receiver with Display and Vibrator. 457.575MHz  H914T Pocket Receiver with	3006220002	Display and Vibrator. 457.575	
2630400004 Vibrator, without Display. 469.250Mhz  EX U914T Pocket Receiver with Vibrator, without Display 412- 427 MHz  EX U914T, Pocket Receiver with Display and Vibrator. 457.575MHz  H914T Pocket Receiver with	2310213002	Display and Vibrator 457.525	
2630400001 Vibrator, without Display 412- 427 MHz  EX U914T, Pocket Receiver with Display and Vibrator. 457.575MHz  H914T Pocket Receiver with	2630400004	Vibrator, without Display.	
3006120012 with Display and Vibrator. 457.575MHz  H914T Pocket Receiver with	2630400001	Vibrator, without Display 412-	
3006220004	3006120012	with Display and Vibrator.	
	3006220004		

### **ACCESSORIES**

	PENLIGHT BATTERY TYPE	
3006120014	IEC LR03 (AAA) (1 PER	
	RECEIVER)	

page 2/2