



1200300100

INTEGRA-10

PAVA Wall Mount System (10 amp channels pre installed)

INTEGRA-10 Public Adress and Voice Alarm

- EN 54-16 CERTIFIED
- SELF-CONTAINED WALL MOUNT PAVA SYSTEM
- SIMPLE INSTALLATION WITH MOUNTING FOR BATTERIES
- PRE-INSTALLED WITH 10 AMPLIFIER CHANNELS, EACH CAPABLE OF UP TO 500W @100V
- ✓ UP TO A TOTAL, 2000W @ 100V PER INTEGRA
- HIGH QUALITY PROFESSIONAL AUDIO PROCESSING
- 24 BIT 48 kHz AUDIO PROCESSING
- 12 ANALOGUE AUDIO INPUTS & OUTPUTS / 6 IP AUDIO INPUTS
- ON BOARD GENERAL PURPOSE INPUTS & OUTPUTS
- FLEXIBLE CONTROL OPTIONS
- INTEROPERABILITY WITH THE VIPEDIA RANGE







Civil Defence Approval



EN 54 Certified

Description

The INTEGRA-10 Public Adress and Voice Alarm all-in-one network enabled voice alarm solution is available with ten channels of pre-installed amplification.

The unit has 12 audio inputs and internal storage for up to 64 recorded messages. With a maximum power of 2000W, integrated audio-over-IP networking, powerful audio processing, and integrated battery charger and battery mounting shelf all in a compact wall-mount enclosure, INTEGRA provides a complete voice alarm solution for both medium to large centralised and decentralised PAVA systems.

Up to 32 INTEGRA can be linked by IP to enable broadcasts from any location to any combination of zones in large decentralised systems. The network switch (NETWORK-SWITCH-LP01) forms a voice alarm compliant ring network topology and can be easily mounted inside the enclosure.

Any INTEGRA variant and the rack mount equivalent VIPEDIA range interoperate seamlessly.

Accessories

page 1/2

certified to meet the requirements in NS-EN ISO 9001. Zenitel reserves the right to modify designs and alter specifications without notice.



NETWORK-SWITCH-LP01

PAVA Network Switch - Layer 2

RMR01	from	datasheet
ו טכוויוכ	11 0111	ualasiieel

BMB01

Din Rail Mount I/O Expansion Device

from site	

D150

PAVA 150W Power Amplifier Module for the V2000 / INTEGRA

from site

D500

PAVA 500W Power Amplifier Module for the V2000 / INTEGRA



LSZDC

PAVA Amplifier Interface Module for the V2000 / INTEGRA

page 2/2