

1200410301

MPS30-GO-AN

Desk Mount Paging and Emergency Mic with 30 Buttons - Gooseneck



- ✓ SUPERSEDED BY THE MPS30-G, SUPPORTING BOTH ANALOGUE AND IP CONNECTIVITY

Description

The MPS30 is a powerful and flexible 30 button paging and or emergency microphone which can provide live, store-and-forward, and recorded message broadcast into user selected zones. Including EN 54 compliant emergency functions and all mandatory indicators and controls.

It consists of a sloping desk console with a flexible gooseneck paging microphone, graphic LCD display, and silent operation 'Touch to Talk' touch pad PTT button. PA zone selection is provided by the Select buttons or by using the rotary selector and graphic LCD display. There is also a VU bar-graph which displays the microphone signal level.

The MPS range can be connected directly to either one or two ASL audio routers using analogue audio and a serial link. All interconnecting cabling and the microphone capsule are continuously monitored.

As well as the main microphone gooseneck, there is a 3.5mm jack plug connection for an auxiliary audio input, such as for background music, and for connection of a microphone headset. A general purpose local contact input and output enables use with PTT foot switches and external speak-now indicators.

The MPS microphone range can be used freestanding on a desk as standard, or can be permanently mounted with the optional mounting bracket MPX. This bracket gives options to mount the microphone flat on a wall, built onto consoles or fixed on desks.

The MPS can be purchased with a fist microphone replacement for the standard gooseneck if required. Please contact Zenitel for more details.

Accessories



VIPEDIA-BOA01

Din Rail Mount RJ45 Breakout Adapter - Single Port




VIPEDIA-BOA02

Din Rail Mount RJ45 Breakout Adapter - Four Port



MPX10

Expansion Module for MPS01 with 10 buttons



MPX10-MB

Wall or desk mount bracket kit for MPS10 and MPS20 microphones

Used With



VIPEDIA-12-NET

PAVA Audio router with network card



VIPEDIA-12-PRO

PAVA Audio router with network card - Dante Enabled



INTEGRA-03

Wall Mount PAVA System (3 amps)



INTEGRA-05

PAVA Wall Mount System (5 amp channels pre installed)



INTEGRA-07

PAVA Wall Mount System (7 amp channels pre installed)



INTEGRA-10

PAVA Wall Mount System (10 amp channels pre installed)



INTEGRA-PRO-03

PAVA Wall Mount System (3 amp channels pre installed) - Dante Enabled



INTEGRA-PRO-05

PAVA Wall Mount System (5 amp channels pre installed) - Dante Enabled



INTEGRA-PRO-07

PAVA Wall Mount System (7 amp channels pre installed) - Dante® Enabled



INTEGRA-PRO-10

PAVA Wall Mount System (10 amp channels pre installed) - Dante® Enabled