



1200300000

INTEGRA-00

Wall Mount PAVA System (0 amp channels pre installed)

- ✓ EN 54-16 CERTIFIED
- ✓ SELF-CONTAINED WALL MOUNT PAVA SYSTEM
- ✓ SIMPLE INSTALLATION
- ✓ PRE-INSTALLED WITH 0 AMPLIFIER CHANNELS
- ✓ UP TO 2000W @ 100V TOTAL POWER
- ✓ HIGH QUALITY PROFESSIONAL AUDIO PROCESSING
- ✓ 24 BIT 48 kHz AUDIO PROCESSING
- ✓ 12 ANALOGUE AUDIO INPUTS & OUTPUTS / 6 IP AUDIO INPUTS
- ✓ ON BOARD GENERAL PURPOSE INPUTS & OUTPUTS
- ✓ FLEXIBLE CONTROL OPTIONS
- ✓ INTEROPERABLE WITH THE VIPEDIA RANGE



Public Address



Voice Alarm

Commercial Audio



Civil Defence Approval

EN54

EN 54 Certified

Description

The INTEGRA-00 all-in-one network enabled voice alarm solution has no amplifier channels pre-installed, this allows for complete amplifier channel customization.

The unit has 12 audio inputs and internal storage for up to 64 recorded messages. With a maximum power of 2000W, integrated audio-over-IP networking, powerful audio processing, and integrated battery charger and battery mounting shelf all in a compact wall-mount enclosure, INTEGRA provides a complete voice alarm solution for both medium to large centralised and decentralised PAVA systems.

Up to 32 INTEGRA can be linked by IP to enable broadcasts from any location to any combination of zones in large decentralised systems. The network switch (NETWORK-SWITCH-LP01) forms a voice alarm compliant ring network topology and can be easily mounted inside the enclosure. Any INTEGRA variant and the rack mount equivalent VIPEDIA range interoperate seamlessly.

Specifications

For full details see Documents

POWER

AC Supply Voltage	230V (+25% / -16%)
AC Supply Frequency	50 / 60 Hz
Quiescent Current (no amplifiers)	525mA
Quiescent Current (per amplifier)	23mA
Maximum Audio Output Power	2000W

Accessories



[BMB01 from datasheet](#)

BMB01

Din Rail Mount I/O Expansion Device

Item Number: 1200550030

[from site](#)

D150

PAVA 150W Power Amplifier Module for the V2000 / INTEGRA

Item Number: 1200202150

[from site](#)

D500

PAVA 500W Power Amplifier Module for the V2000 / INTEGRA

Item Number: 1200202500

NETWORK-SWITCH-LP01

PAVA Network Switch - Layer 2

Item Number: 1200571000



LSZDC

PAVA Amplifier Interface Module for the V2000 / INTEGRA

Item Number: 1200540000