



2310102077

# VR1T Power Converter 24VDC/AC to 12VDC/1A

Power Converter

- 24VAC or 24VDC Input Voltage
- 12VDC Output Voltage
- Input LED

## Description

The VR1T Power Converter 24VDC/AC to 12VDC/1A converts a 24VAC or 24VDC input into a regulated 12VDC output. It provides power for 12VDC CCTV cameras and accessories. The quick release terminals facilitate ease of wiring and the compact design allows for integration in a wide range of camera housings.

page 1/2

## **Specifications**

#### **SPECIFICATIONS**

Input Voltage	24VAC or 24VDC
Output Voltage	12VDC
Output Current	1A continuous supply current
Output (Other)	Built-in overload protection. Filtered and regulated.
Indicators (LED)	Input LED
Agency Listings	CE European Conformity

#### PHYSICAL AND ENVIRONMENTAL

Dimensions (L x W x H)	41.28mm x 60.32mm x 25.4mm
Product Weight	0.06 kg
Shipping Weight	0.14 kg
Operating Temperature	0°C to 49°C
Storage Temperature	-20°C to 70°C
Relative Humidty	85% +/-5%
BTU/Hr. (approx.)	6 BTU/Hr.

### **Used With**







#### SH50H

Camera Seahawk Maritime colour, 12VDC, 50deg, IP66/IP67

#### SH80H

Camera Seahawk Maritime colour, 12VDC, 80deg, IP66/IP67

#### SH107H

Camera Seahawk Maritime colour, 12VDC, 107deg, IP66/IP67